

System Messages ESY5600 - ESY5699

Message	Explanation	Action
ESY5600 - Unknown function.	An invalid value was specified in the FUNCTION field.	Specify valid FUNCTION value.
ESY5602 - Device is invalid.	An invalid DEVICE value was specified.	Specify valid DEVICE value.
ESY5603 - INDEX / ALIAS missing.		Specify INDEX / ALIAS.
ESY5604 - No volumes specified.	No VOLUMES were specified for CATLG / RECATLG.	Specify VOLUMES.
ESY5605 - IGWASMS returned with RC :1: and reason :2:.	A request failed to retrieve attributes for a dataset.	Contact your systems programmer.
ESY5606 - Managed datasets cannot be uncataloged.	A request was issued to uncatalog an SMS-managed dataset.	Do not ask to uncatalog an SMS-managed dataset.
ESY5610 - QNAME is missing.	No value was specified in the QNAME field.	Specify valid QNAME value.
ESY5611 - QNAME cannot start with SYS.	Major names beginning with SYS are not allowed.	Specify valid QNAME value.
ESY5612 - RNAME is missing.	No value was specified in the RNAME field.	Specify RNAME value.
ESY5613 - RNAME length is missing or invalid.	No value was specified in the RNAME-LENGTH field.	Specify valid RNAME-LENGTH value.
ESY5614 - Resource is in use.	Resource is already allocated as shareable by another task, and exclusive access was requested.	Retry at a later time.
ESY5615 - Resource held by another task.	Resource is already allocated exclusively by another task.	Retry at a later time.
ESY5616 - Error in GQSCAN routine.	An internal error occurred as a result of the GQSCAN macro request.	Notify systems programmer. (Software AG technical support should be notified as well).
ESY5621 - Identifier missing/duplicate/not found.	The identifier associated with the area was missing/duplicate/not found.	Specify correct identifier.
ESY5622 - NUMBER-OF-ENTRIES missing or invalid.	The specification of the maximum number of entries was missing/invalid.	Specify a valid NUMBER-OF-ENTRIES value.
ESY5623 - ENTRY-LENGTH missing or invalid.	The specification of the entry length was missing/invalid.	Specify a valid ENTRY-LENGTH value.
ESY5624 - ENTRY-NUMBER missing or invalid.	The specification of the entry number was missing/invalid.	Specify correct entry number.
ESY5625 - Cannot allocate area.	Insufficient storage was available to allocate the area.	Decrease amount of requested storage or notify systems programmer.

Message	Explanation	Action
ESY5626 - DATA missing.	No data was specified.	Specify the DATA field.
ESY5627 - Field position + length > 250.	The field extends the maximum area length (250).	Specify valid field position/length.
ESY5628 - Error in editor.	An internal editor error occurred.	Notify systems programmer.
ESY5629 - Area is protected.	Area is protected.	No action required.
ESY5630 - Console not defined or not active.	The specified console ID was not found.	Specify valid console ID.
ESY5631 - Console table not found.	Console table could not be found.	Contact your systems programmer.
ESY5632 - General or Control object not found.	General or Control object returned by Multi Console Support (MCS) could not be found.	Contact your systems programmer.
ESY5633 - Cannot lock Console table.	Console table could not be locked for exclusive use.	Retry operation. If problem persists, please contact your systems programmer.
ESY5634 - Invalid record number.	Requested record number is invalid.	Retry operation. If problem persists, please contact your systems programmer.
ESY5635 - Attempt to alter key in KSDS file.	Modifying keys in KSDS files is not allowed.	Check program and correct error.
ESY5636 - Too many active requests on this ACB.	There may be a nested loop while accessing VSAM files or there are too many parallel requests open.	Check your program and check also with your ESY-DBA.
ESY5637 - VSAM subtask is not active.	The ESY subtask for VSAM access may be abended. Check with your ESY-DBA to restart ESY.	Contact your ESY-DBA or contact Software AG technical support.
ESY5638 - Key not found.	Key to access the requested record in your file not found.	Check program and correct error.
ESY5639 - Cannot delete record in ESDS file.	Deleting records from ESDS files is not allowed.	Check program and correct error.
ESY5640 - Error generating VSAM control blocks.	An error occurred generating VSAM control blocks.	Notify systems programmer.
ESY5641 - Error :1: while opening SMF or VSAM file.	A VSAM error occurred while opening an SMF file.	Notify systems programmer.
ESY5642 - Error :1: while reading SMF or VSAM file.	A VSAM error occurred while reading an SMF file.	Notify systems programmer.
ESY5643 - SMF not active / not recording.	At the time of the request SMF is not active / not recording.	Notify systems programmer.
ESY5644 - xxxxxxxx error in POWER interface aabb.	Error aabb returned by POWER interface function xxxxxxxx.	Contact systems programmer.
ESY5645 - Invalid RBA was specified.	The requested RBA was not found.	Specify valid RBA value.

Message	Explanation	Action
ESY5646 - Write to VSAM only allowed on base cluster.	An attempt was made to write to a none-base cluster.	Check program and correct error.
ESY5647 - VSAM cluster is not defined as reusable.	Access to VSAM cluster only allowed if reusable.	Define your VSAM cluster reusable.
ESY5648 - Record not in ascending key sequence.	An attempt was made to write a record with a wrong key.	Check program and correct error.
ESY5649 - ESY User not found or cannot be cancelled.	The ESY user could not be found for various functions.	Correct input data.
ESY5650 - Invalid sequential file.	The requested sequential file does not exist.	Please check file name and rerun program.
ESY5651 - Requested catalog does not exist.	The requested CVOL does not exist.	Specify valid CVOL.
ESY5652 - Catalog structure inconsistent.	The catalog structure is inconsistent.	Notify the systems programmer.
ESY5653 - Cannot delete index.	The index cannot be deleted.	No action is required.
ESY5654 - Index structure does not exist.		No action is required.
ESY5655 - Insufficient space on catalog dataset.	The catalog dataset is full.	Notify the systems programmer.
ESY5656 - Error cataloging generation dataset.	An error occurred while cataloging a generation dataset.	Check specified values. If valid, contact the systems programmer.
ESY5657 - I/O error on catalog.	An I/O error occurred while accessing the catalog.	This is probably a hardware error. Contact the systems programmer.
ESY5658 - dataset is not cataloged.	The specified dataset is not cataloged.	No action is required.
ESY5659 - dataset is already cataloged.	The specified dataset is already cataloged.	No action is required.
ESY5660 - :1: - :2: module not available.	The specified Natural module was not found.	Specify name of an existing Natural module.
ESY5661 - :1: - Natural sub-task already active.	A Natural subtask is already active for this user.	Make sure that subtask is closed prior restarting it.
ESY5662 - :1: - Natural sub-task not allowed.	The Natural subtask system has not been initialized.	Notify systems programmer.
ESY5663 - :1: - Natural sub-task not active.	The Natural subtask does not exist.	No action is required.
ESY5664 - :1: - Natural sub-task table full.	The maximum number of Natural subtasks is reached.	Notify systems programmer.
ESY5665 - :1: - invalid action requested.	An invalid action was requested.	Specify valid action.
ESY5666 - :1: - Natural sub-task must have parameters.	An attempt was made to start a Natural subtask without parameters.	Specify parameter for Natural subtask.

Message	Explanation	Action
ESY5669 - Queue or job name invalid.	Submit JCL contains error.	Correct JCL error and rerun program.
ESY5670 - View not supported.	This view is not supported on the local operating system.	
ESY5671 - Class missing or is invalid.	The function CHANGE requires a valid NEW-CLASS, NEW-DESTINATION or NEW-USERID value.	
ESY5672 - Segment option requires JOBNAM/JOBNUMBER.	Specifying the SEGMENT option (SEGMENT-NUMBER > 0) requires that the job is identified with JOB-NAME and JOB-NUMBER.	
ESY5673 - Access error due to FILETABLE=STATIC.	The requested file could not be accessed because the Entire System Server startup parameter FILETABLE was specified as STATIC. Only those files available at ESY initialization time (STD,PARSTD & TEMP labels) can therefore be accessed.	To allow dynamic access of files NOT specified at ESY initialization time, change the FILETABLE parameter to DYNAMIC and restart Entire System Server.
ESY5674 - VTOC error reading format-3 labels.	VTOC error reading format-3 labels for the requested file.	Information message only. No action necessary or possible.
ESY5675 - :1: not supported.	Entire System Server has detected that the requested file has attributes which are not supported by this version of ESY e.g. Multi-volume files, Multi-extent output files etc.	
ESY5676 - Not first volume of a multi-volume file.	Entire System Server has detected that the file on the specified volume is NOT the first volume/extent of a multi-volume file.	
ESY5678 - Member already exists.	In WRITE-FILE or COPY-FILE, REPLACE = 'NO' was specified, however the member exists.	No action is required
ESY5679 - Input and output files are incompatible.	COPY-FILE has determined that the record formats of the input and output files are not compatible (RECFM does not match, block size incompatibilities, etc.).	Verify dataset attributes and reissue request with correct parameters.
ESY5680 - Job/output is protected.	The user is not authorized to access the specified job/output.	Notify systems programmer.
ESY5681 - Job/output is active.	The specified job/output is currently active.	There is no action required.
ESY5682 - Job/output is not dispatchable.	The job/output is not dispatchable.	There is no action required.
ESY5683 FAMS error, R15=:1:, R0=:2:.	A FAMS error occurred while COPY-FILE was copying one or more program objects.	Check the console log for IGW prefixed messages issued by FAMS for further information.

Message	Explanation	Action
ESY5684 Remote program object copy currently unsupported.	In this release of Entire System Server, use of COPY-FILE on OS/390 for copying program objects between different nodes is not supported. This message is also issued if a program object copy request is issued to a VSE/ESA node.	A workaround is to first copy the program object to a PDS on the local mode, then copy to a PDS on the remote node, then copy to the target PDSE on the remote node.
ESY5685 CPOOL LIST Return Code 2	The CPOOL LIST service used by COPY-FILE returned Code 2, which indicates an internal error. This occurred when you performed a program object copy using COPY-FILE and there were aliases for the object	Contact Software AG technical support
ESY5687 - Bad variable record.	Bad variable record.	No action is required.
ESY5688 - Return code :1: HCF function :2:.	The HCF function failed. The return code is the HCF return code.	Notify systems programmer.
ESY5690 - 1: error :2: during :3:.	An error occurred accessing PANVALET or LIBRARIAN data.	Notify systems programmer.
ESY5691 - Error while accessing librarian member.	An error occurred accessing a LIBRARIAN member.	There is no action required.
ESY5692 - You are not permitted to access member.	This user is not authorized to access the specified member.	Check with systems programmer.
ESY5693 - :1:.	A PANVALET error occurred.	See message text.
ESY5694 - Strange error opening VTOC.	A strange internal error occurred reading the VTOC.	Notify systems programmer.
ESY5695 - VTOC is in use.	The VTOC is currently in use.	Retry.
ESY5696 - Cannot assign logical unit.	A logical unit could not be assigned.	Notify systems programmer.
ESY5697 - Library/sublibrary not found.	The specified library/sublibrary was not found.	Specify valid library/sublibrary name.
ESY5698 - Internal LIBRARIAN error has occurred.	An internal LIBRARIAN error occurred.	Notify systems programmer.
ESY5699 - Not enough main storage available.	Not enough main storage was available to process the request.	Notify systems programmer.